EE 3054 - Fall 2012

Quiz 4 (Discrete-time systems)

1. An LTI system has impulse response

$$h(n) = 2\,\delta(n) + 3\,\delta(n-1) - \delta(n-2).$$

Write a difference equation to implement the system.

2. An LTI system has impulse response

$$h(n) = 2\,\delta(n) + \left(\frac{2}{3}\right)^n u(n).$$

Write a difference equation to implement the system.

3. A causal LTI system is implemented by the difference equation

$$y(n) = x(n) + \frac{3}{2}y(n-1) - \frac{1}{2}y(n-2).$$

- (a) Find the transfer function H(z).
- (b) Find the impulse response h(n).
- (c) Classify the system as stable/unstable.
- (d) Find and sketch the impulse response g(n) of the stable inverse system.

4. An LTI system has impulse response

$$h(n) = -\delta(n) + \frac{5}{2}\delta(n-1) - \delta(n-2).$$

Find the impulse response g(n) of the <u>stable</u> inverse system. Accurately sketch g(n) for $-3 \le n \le 2$.

5. Two causal LTI systems are combined in parallel:



The two systems are implemented with difference equations:

$$H_1: \quad f(n) = 2x(n) - \frac{1}{2}f(n-1)$$
$$H_2: \quad g(n) = x(n) - \frac{1}{3}g(n-1)$$

Find the difference equation describing the total system between input x(n) and output y(n).